


L-Tune version 3.15**Project name:****Requested parameters**

Luminaire	Mini Luma
Colour temperature	Neutral White
Flux	6 500 lm @ ConstaFlux
Requested lumen depreciation	ConstaFlux
Requested expected lifetime	75 000 hours
Dim option	DYNADIM
Dim regime or percentage	4A
Dynadim location	SLOVAKIA

Calculated possible solutions

Solutions	ConstaFlux Requested
Mini Luma 30 LED	3 043 kWh
Mini Luma 40 LED	2 743 kWh
In grey indicative alternative solutions in other luminaire types. Redo your lighting calculation with photometry of preferred type. 	
Luma 1 40 LED	2 735 kWh
Luma 1 48 LED	2 638 kWh
Luma 1 60 LED	2 580 kWh
Luma 1 68 LED	2 546 kWh
Luma 2 60 LED	2 572 kWh

Lowest initial investment **possibility** based on input dataMost energy efficient **option** based on input data**Solution** with lowest total energy consumption (kWh over requested expected lifetime)☐ Only show results with Power Factor 0.90 or higher

Please note: * If only Blue and Green are shown, the Green solution represents the Yellow option as well.

** If only one solution appears it is shown Green (Blue, Yellow and Green are within the same solution).

Results**Option Blue 1: Mini Luma 30 LED - ConstaFlux**

Luminaire type	Mini Luma
Number of LED	30 LED
System power (minimum)	62 W
System power (maximum)	66 W
Consumed power over lifetime	3 043 kWh
Minimal realized flux	6 500 lm
Power Factor (100%)	0.97
Driver Code	C00
Program Code	IJPMLKT3WQCH

Option Green 1: Mini Luma 40 LED - ConstaFlux

Luminaire type	Mini Luma
Number of LED	40 LED
System power (minimum)	56 W
System power (maximum)	59 W
Consumed power over lifetime	2 743 kWh
Minimal realized flux	6 500 lm
Power Factor (100%)	0.94
Driver Code	D00
Program Code	JUIPLKT3WQC3

Indal
Lighting for you

www.indal-lighting.com